

```
service password-encryption
service timestamps debug
!
hostname router
!
enable password 7 Pj1SpBlibw/blcJ
!
username Akiwei password 7 WJVNV6BVewPmiELA
!
interface fastethernet 0/0
encapsulation ppp
ip address negotiated
ip mtu 1492
ip nat outside
no cdp enable
dialer in-band
dialer-group 1
ppp pap sent-username 100000232137 password 7 yMWUzdygmy2QCQ0vOA(100000232137
is virtual, Should add ADSL logon account ,yMWUzdygmy2QCQ0vOA is logon password)
line auto-reset
line auto-dial
h323-gateway voip id test ipaddr 13.55.66.77 1719
h323-gateway voip interface
h323-gateway voip h323-id 1234
h323-gateway voip bind srcaddr 0.0.0.0
!
interface ethernet 0/0
ip address 192.168.0.1 255.255.255.0
ip nat inside
!
interface async 0/0
!
line vty 0 31
!
ip route 0.0.0.0 0.0.0.0 fastethernet 0/0 type4
ip nat pool p1 0.0.0.0 0.0.0.0 prefix-length 32
ip nat inside source list 1 pool p1 overload
!
access-list 1 permit any
dialer-list 1 protocol ip permit
voice-port 1/0
!
voice-port 1/1
!
voice-port 1/2
!
voice-port 1/3
!
voice-port 2/0
!
voice-port 2/1
!
voice-port 2/2
!
voice-port 2/3
!
dial-peer voice 1001 pots
destination-pattern 075570000051
port 1/0
!
dial-peer voice 1002 pots
destination-pattern 075570000052
port 1/1
!
dial-peer voice 1003 pots
destination-pattern 075570000053
port 1/2
!
dial-peer voice 1004 pots
destination-pattern 075570000054
port 1/3
!
dial-peer voice 1005 pots
destination-pattern 075570000055
port 2/0
!
dial-peer voice 1006 pots
destination-pattern 075570000056
port 2/1
!
dial-peer voice 1007 pots
destination-pattern 075570000057
port 2/2
!
dial-peer voice 1008 pots
```

```
destination-pattern 075570000058
port 2/3
!
dial-peer voice 100 voip
destination-pattern T
codec g723r63
session target ras
no vad
!
dial-peer terminator #
gateway
!
!
end
```